

Date

Name

Client

Project name

Quote#


Type/Quantity

26/05/2020 19:11:22

Specification Sheet

NIME 930

26411 9300

[Weblink](#)

Cutout shape/size:  Ø KIT mm

Recessed depth: 150 mm

Available colors: PRIMER (26411 9300 PRIM)

ADJUSTABLE 0-30°/355°

INCL. 1 x LED 4,1-11,4W / CRI>90 / 3000K / 380-808lm

INCL. 1 x ADJUSTABLE BEAM 20°-40°

EXCL. LED POWER SUPPLY 900mA-DC

Other CRI or KELVIN on request

LED Technics: Light source: 808 lm // 11 W // 74 lm/W
Luminaire: 13 W

Class: III

Weight: 0.8 KG

Protection level: IP20


Minimum distance: n.a.

Requirements: MOUNTING KIT NIME O.F.A.
LED POWER SUPPLY 350 / 500 / 700 / 900mA-DC DIM


For detailed installation instructions, please consult the manual.

NIME 930
26411 9300


Ceiling compatibility



System ceiling











Plasterboard




Stucanet


NIME 930
26411 9300

Related references
LED POWER SUPPLIES


Weblink / Specs sheet  LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 300 90 67 Number of luminaires: 3 / 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 300 48 350 ED1 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 300 48 350 ED5 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL 300 48 350 MDL Number of luminaires: 3
Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL 300 48 350 WDL Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 300 48 500 ED1 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 300 48 500 ED5 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL 300 48 500 MDL Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO DIM1
300 48 500 PRO ED1
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO DIM5
300 48 500 PRO ED5
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO WDL
300 48 500 PRO WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL
300 48 500 WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM1
300 48 700 ED1
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5
300 48 700 ED5
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W MDL
300 48 700 MDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO DIM1
300 48 700 PRO ED1
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO DIM5
300 48 700 PRO ED5
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO WDL
300 48 700 PRO WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W WDL
300 48 700 WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 10W DIM8
300 90 110
220-240V / 50-60Hz
Number of luminaires: 2 -> 2

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 15W
300 90 91
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 3 (2)

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 16W DIM8
300 90 3112
110-240V / 50-60Hz
Number of luminaires: 2 -> 3 (3)

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 18W DIM8
300 90 116
220-240V / 50-60Hz
Number of luminaires: 3 -> 4

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 8W
300 90 108
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 1 (1)

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 11W DIM8
300 90 119
220-240V / 50-60Hz
Number of luminaires: 1 -> 1

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 20W DIM8
300 90 121
220-240V / 50-60Hz
Number of luminaires: 2 -> 3

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 21W
300 90 92
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 3 (1)

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 22W DIM8
300 90 5120
110-240V / 50-60Hz
Number of luminaires: 3 -> 3 (3)

[Weblink / Specsheet](#)


LED POWER SUPPLY 700mA-DC / 17W
300 90 95
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 1 (1)

[Weblink / Specsheet](#)

LED POWER SUPPLY 700mA-DC / 20W DIM8
300 90 118
220-240V / 50-60Hz
Number of luminaires: 2 -> 2


[Weblink / Specsheet](#)

LED POWER SUPPLY 700mA-DC / 36W DIM8
300 90 123
220-240V / 50-60Hz
Number of luminaires: 1 -> 3

[Weblink / Specsheet](#)


LED POWER SUPPLY MULTI POWER
21012 0010
220-240V / 0/50-60Hz
Number of luminaires: 2 -> 3 / 3 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI POWER DIM1
21012 0021
220-240V / 0/50-60Hz
Number of luminaires: 4 / 4 / 3 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI POWER DIM5
21012 0035
220-240V / 0/50-60Hz
Number of luminaires: 4 / 4 / 4 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER COMPACT WDL
21012 009W
220-240V / 0/50-60Hz
Number of luminaires: 4 / 4 / 3 / 3

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM5
300 90 68
110-240V / 0/50-60Hz
Number of luminaires: 3 (3) / 3 (2) / 3 (1) / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM6
300 90 61
220-240V / 50-60Hz
Number of luminaires: 3 / 3 / 3 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM7
300 90 124
110-240V / 0/50-60Hz
Number of luminaires: 2 -> 4 (3) / 3 (2) / 2 (1) / 1 (1)

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM7
300 90 64
110-240V / 0/50-60Hz
Number of luminaires: 4 (3) / 3 (2) / 3 (1) / 1 (1)

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM9
300 90 63
110-240V / 0/50-60Hz
Number of luminaires: 5 (5) / 5 (5) / 5 (4) / 4 (3)

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER HV
300 90 135
220-240V / 0/50-60Hz
Number of luminaires: 4 -> 6 / 3 -> 6 / 3 -> 6 / 3 -> 5

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER HV DIM7
300 90 134
110-240V / 0/50-60Hz
Number of luminaires: 2 -> 8 (8) / 8 (6) / 6 (4) / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER HV DIM9
300 90 69
110-240V / 0/50-60Hz
Number of luminaires: 2 -> 8 (8) / 8 (6) / 6 (4) / -

[Weblink](#) / [Specsheet](#)



LED POWER SUPPLY MULTI-POWER MINI DIM5
300 90 125
110-240V / 0/50-60Hz
Number of luminaires: 3 (3) / 3 (2) / 2 (1) / -

[Weblink](#) / [Specsheet](#)



LED POWER SUPPLY MULTI-POWER WDL
21012 009W
110-240V / 0/50-60Hz
Number of luminaires: 5 (5) / 5 (5) / 5 (4) / 4 (3)

Related references

MOUNTING KITS NEW CONSTRUCTION

[Weblink](#) / [Specsheet](#)



MOUNTING KIT NIME O.F.A.
26410 0010

Date

Name

Client

Project name

Quote#


Type/Quantity

26/05/2020 18:40:52

Specification Sheet

NIME 927

26411 9200

[Weblink](#)

Cutout shape/size:  Ø KIT mm

Recessed depth: 150 mm

Available colors: PRIMER (26411 9200 PRIM)

ADJUSTABLE 0-30°/355°

INCL. 1 x LED 4,1-11,4W / CRI>90 / 2700K / 355-755lm

INCL. 1 x ADJUSTABLE BEAM 20°-40°

EXCL. LED POWER SUPPLY 900mA-DC

Other CRI or KELVIN on request

LED Technics: Light source: 755 lm // 11 W // 69 lm/W
Luminaire: 13 W

Class: III

Weight: 0.8 KG

Protection level: IP20


Minimum distance: n.a.

Requirements: MOUNTING KIT NIME O.F.A.
LED POWER SUPPLY 350 / 500 / 700 / 900mA-DC DIM


For detailed installation instructions, please consult the manual.

NIME 927
26411 9200


Ceiling compatibility



System ceiling



Plasterboard












Stucanet

NIME 927
26411 9200


Related references

LED POWER SUPPLIES


Weblink / Specs sheet  LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 300 90 67 Number of luminaires: 3 / 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 300 48 350 ED1 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 300 48 350 ED5 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL 300 48 350 MDL Number of luminaires: 3
Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL 300 48 350 WDL Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 300 48 500 ED1 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 300 48 500 ED5 Number of luminaires: 3	Weblink / Specs sheet  LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL 300 48 500 MDL Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO DIM1
300 48 500 PRO ED1
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO DIM5
300 48 500 PRO ED5
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W PRO WDL
300 48 500 PRO WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL
300 48 500 WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM1
300 48 700 ED1
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5
300 48 700 ED5
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W MDL
300 48 700 MDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO DIM1
300 48 700 PRO ED1
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO DIM5
300 48 700 PRO ED5
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO WDL
300 48 700 PRO WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W WDL
300 48 700 WDL
Number of luminaires: 3

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 10W DIM8
300 90 110
220-240V / 50-60Hz
Number of luminaires: 2 -> 2

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 15W
300 90 91
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 3 (2)

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 16W DIM8
300 90 3112
110-240V / 50-60Hz
Number of luminaires: 2 -> 3 (3)

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 18W DIM8
300 90 116
220-240V / 50-60Hz
Number of luminaires: 3 -> 4

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 8W
300 90 108
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 1 (1)

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 11W DIM8
300 90 119
220-240V / 50-60Hz
Number of luminaires: 1 -> 1

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 20W DIM8
300 90 121
220-240V / 50-60Hz
Number of luminaires: 2 -> 3

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 21W
300 90 92
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 3 (1)

[Weblink / Specsheet](#)


LED POWER SUPPLY 500mA-DC / 22W DIM8
300 90 5120
110-240V / 50-60Hz
Number of luminaires: 3 -> 3 (3)

[Weblink / Specsheet](#)


LED POWER SUPPLY 700mA-DC / 17W
300 90 95
110-240V / 0/50-60Hz
Number of luminaires: 1 -> 1 (1)

[Weblink / Specsheet](#)

LED POWER SUPPLY 700mA-DC / 20W DIM8
300 90 118
220-240V / 50-60Hz
Number of luminaires: 2 -> 2


[Weblink / Specsheet](#)

LED POWER SUPPLY 700mA-DC / 36W DIM8
300 90 123
220-240V / 50-60Hz
Number of luminaires: 1 -> 3

[Weblink / Specsheet](#)


LED POWER SUPPLY MULTI POWER
21012 0010
220-240V / 0/50-60Hz
Number of luminaires: 2 -> 3 / 3 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM1
21012 0021
220-240V / 0/50-60Hz
Number of luminaires: 4 / 4 / 3 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM5
21012 0035
220-240V / 0/50-60Hz
Number of luminaires: 4 / 4 / 4 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER COMPACT WDL
21012 009W
220-240V / 0/50-60Hz
Number of luminaires: 4 / 4 / 3 / 3

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM5
300 90 68
110-240V / 0/50-60Hz
Number of luminaires: 3 (3) / 3 (2) / 3 (1) / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM6
300 90 61
220-240V / 50-60Hz
Number of luminaires: 3 / 3 / 3 / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM7
300 90 124
110-240V / 0/50-60Hz
Number of luminaires: 2 -> 4 (3) / 3 (2) / 2 (1) / 1 (1)

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM7
300 90 64
110-240V / 0/50-60Hz
Number of luminaires: 4 (3) / 3 (2) / 3 (1) / 1 (1)

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER DIM9
300 90 63
110-240V / 0/50-60Hz
Number of luminaires: 5 (5) / 5 (5) / 5 (4) / 4 (3)

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER HV
300 90 135
220-240V / 0/50-60Hz
Number of luminaires: 4 -> 6 / 3 -> 6 / 3 -> 6 / 3 -> 5

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER HV DIM7
300 90 134
110-240V / 0/50-60Hz
Number of luminaires: 2 -> 8 (8) / 8 (6) / 6 (4) / -

[Weblink](#) / [Specsheet](#)




LED POWER SUPPLY MULTI-POWER HV DIM9
300 90 69
110-240V / 0/50-60Hz
Number of luminaires: 2 -> 8 (8) / 8 (6) / 6 (4) / -

[Weblink](#) / [Specsheet](#)



LED POWER SUPPLY MULTI-POWER MINI DIM5
300 90 125
110-240V / 0/50-60Hz
Number of luminaires: 3 (3) / 3 (2) / 2 (1) / -

[Weblink](#) / [Specsheet](#)



LED POWER SUPPLY MULTI-POWER WDL
21012 009W
110-240V / 0/50-60Hz
Number of luminaires: 5 (5) / 5 (5) / 5 (4) / 4 (3)

Related references

MOUNTING KITS NEW CONSTRUCTION

[Weblink](#) / [Specsheet](#)



MOUNTING KIT NIME O.F.A.
26410 0010